

PIR DETECTOR VIA RADIO



- VESTA radio PIR detector
- 15 meter coverage, 130 °
- 45 kg anti-pet (configurable remotely)
- Automatic PIR sensor calibration
- Double detection function configurable from App Installer
- 2 levels of sensitivity (remotely configurable)
- Efficient dwell time between detections
- Optional swivel bracket
- It works with 1 CR123 battery
- 5.8 year battery life
- Grade 2 certificate

**Reference / Model****VESTA-177 / IR-35SL-F1**

specs

Detection range: 15 meters, 130 °
Automatic PIR sensor calibration
It has a double detection function (the alarm is confirmed in case of two detections in a short time), configurable from the Installer App
Efficient standby time between detections
RF frequency: 868MHz
Microprocessor controlled with advanced ADSP algorithms for false alarm immunity
Anti-pets up to 45 kg
Two selectable sensitivity levels
Remote configurable sensor sensitivity and anti-pet function
High immunity to false alarms
Tamper Protection
Superior white light and noise rejection
Automatic energy saving mechanism
Random supervisory signals for system integrity
Rejection of radio interference
Sensitivity control with temperature compensation
Works with 1 CR123 battery
5.8 year battery life
-10 ° C ~ + 45 ° C operating temperature
Relative humidity up to 85% (non-condensing)
2.3 ~ 2.5 meter installation height
Optional swivel bracket
Grade 2 Certificate