

VESTA-111N-SF1

HYB-1-S0-2GW-SF1 868



VESTA 2G+IP hybrid alarm system

SF1



GRADE 3

2G



- VESTA hybrid central station up to 640 zones
- Compatible with HD transmission devices (PIRCAMS) and SF1 bidirectional audio
- 2G connectivity (GPRS)
- IP communications (Ethernet)
- 16 expandable wired zones
- Up to 640 zones (wired+radio)
- Up to 8 areas and 320 users
- 1 PGM output
- Up to 4 VESTA-114 keypads
- Configuration by smarthomesec APP or by VESTA-114 keypad
- Grade 3 certified.



Reference / Model

VESTA-111N-SF1 / HYB-1-S0-2GW-SF1 868

2G (GPRS) model

Amplified quick connection for external GPRS antenna (not included, **VESTA-275** or **VESTA-276** recommended)

Advanced automation and home automation management functions

Latest communication technologies: built-in IP module, in addition to 2G

Supports HD streaming devices (PIRCAMS) and SF1 two-way audio

Built-in receiver via F1 868Mhz radio compatible with all F1 devices in the catalog (2 km in open field)

Allows up to 16 wired zones on board expandable via zone expanders

Allows both wired and F1 radio zones (640 zones in total)

Up to 8 areas

Allows up to 4 wired keypads

Up to 240 users

1 siren output, plus 1 simultaneous voltage free output

VESTA-111N-SF1

HYB-1-S0-2GW-SF1 868



VESTA 2G+IP hybrid alarm system

Reference / Model

VESTA-111N-SF1 / HYB-1-S0-2GW-SF1 868

Full programming in less than 10 minutes from web and SmartHomeSec app

Flexibility of wiring and selection of resistance values for each zone

Integration with DAHUA IP cameras

Compatibility with all F1 devices for automatic control of your installation (relays, sockets, sensors, etc.)

Supports indoor and outdoor PIRCAMS, allowing users and central stations to visually verify the alarm

Programming of up to 100 automatic rules (automatic watering, presence simulation, control of any device by calendars, auto-arming, etc.).

Extreme convenience and flexibility in the methods of communication of events and photos to ARC (MANITOU, encrypted MANITOU, CID, SIA, FTP, HTTP)

3A power supply

Voltage for BUS module and wired zones: 13,56V

With VESTA's SmartHomeSec application you can remotely control and manage both your security and video surveillance system and the smart devices in your home.

VESTA's hybrid control panel is compatible with Google Home and Alexa

USB port available to add WiFi, ZigBee or Z-Wave connectivity (see related products)

Integration with Fibaro automatic devices (Fibaro Dimmer 2, Roller Shutter 3, Smart Module, Single Switch 2)

EN50131 Grade 3 certified